

HDMI to Displayport Active Adapter Cable, 1M 2M 3M



Description:

FARSINCE Active HDMI to Mini DisplayPort Adapter Cable is an ideal solution for connecting your HDMI enabled device to a DP monitor, screen, or projector using this active HDMI (male) to DisplayPort (female) video adapter. This DP converter lets users connect a secondary screen or display to their HDMI equipped computer. The adapter also transmits high quality audio and video with resolution up to 4K@60Hz.

Item no. FS11702

Specification:

- Input interface: HDMI Male/ USB 2.0 A Male, gold plated
- Output interface: DisplayPort Male, gold plated
- Cable Conductor: Bare Copper
- Wire Gauge: 30AWG
- Chipset: LT6711A
- Triple Shielding: Individual pair aluminum foil, Overall aluminum foil, braiding
- Jacket: PVC
- Housing: ABS mold
- Supports resolutions up to 3840x2160 @60Hz
- Built-in USB plug provides power if needed
- Compliant: RoHS, REACH

Order Informaiton:

- FS11702-010: 1.0m, 30AWG, OD6.0±0.2mm
- FS11702-020: 2.0m, 30AWG, OD6.0±0.2mm
- FS11702-030: 3.0m, 30AWG, OD6.0±0.2mm